



Our retail price is a recommendation only. Prices in offer may differ. All prices indicated 0,00 € will follow in the offer.

BENNING MULTIMETER MM 1-2 0.1 MV-750 V AC/0.1 MV-1000 V DC RMS

SKU: 4014650440822

Multimeter MM 1-2 0.1 mV-750 V AC/0.1
mV-1000 V DC RMS



Categories: [Measuring and testers for electrical installation](#), [Multimeters and accessories](#)

Product Features: Measuring technique: RMS

Brand: BENNING

Nominal voltage range: 0.1 mV-750 V AC/0.1
mV-1,000 V DC

Measurement category: CAT III 600 V/CAT II
1000 V

[Datasheet](#)

Scope of delivery:

1,00 ST Multimeter MM 1-2 0.1 mV-750 V
AC/0.1 mV-1000 V DC RMS |

PRODUCT DESCRIPTION

With 3½-digit LCD display (2,000 points) and volt sensor

- Integrated volt sensor signals non-contact phase voltages and cable breaks in lines (optical/acoustic)
- Single-pole phase testing
- Automatic and manual range selection
- Measured value memory (HOLD maximum/minimum value memory (MAX/MIN))
- Continuity and diode testing
- Automatic switch-off
- Measurement category: CAT III 600 V, CAT II 1000 V Measuring ranges: Direct voltage: 0.1 mV-1,000 V, alternating voltage: 0.1 mV-750 V, direct current: 1 mA-10 A, alternating current: 1 mA-10 A, resistance: 0.1 -20 M, frequency: 1 Hz-20 MHz, capacitance: 1 pF-2 mF Further technical information:
- Width: 74mm
- Length: 156mm
- Height: 44mm
- Subject to audit: Yes Scope of supply: Supplied with batteries (2 x type AAA measuring leads and bag, replacement batteries see article no. 4000 901 810 Note on the disposal of batteries and rechargeable



batteries As we sell batteries and rechargeable batteries and devices that contain batteries and rechargeable batteries, under the German Battery Act (BattG) we are obliged to draw your attention to the following: The symbol of the waste bin with the X through it on batteries and rechargeable batteries means that they must not be disposed of in household waste after consumption. If batteries or rechargeable batteries contain mercury, cadmium or lead, you will find the chemical symbol (Hg, Cd or Pb) under the symbol of the waste bin with the X through it. Every user of batteries or rechargeable batteries is legally obliged to return old batteries and rechargeable batteries. They can be returned, free of charge, to the retailer or another collection point near you. You can obtain the addresses of suitable collection points near you from your local government authority. In the case of batteries that contain more than 0.0005 percent by mass mercury, more than 0.002 percent by mass cadmium or more than 0.004 percent by mass lead, the chemical symbols of the respective harmful substance used are indicated under the waste bin symbol. The chemical symbols have the following meaning: Pb: Battery contains lead Cd: Battery contains cadmium Hg: Battery contains mercury

PRODUCT DATASHEET LEGAL NOTE

Please note that the information on this datasheet is provided without warranty and is intended only as non-binding information about the product. Any liability for damages or losses that may arise from the use of this information is excluded. We therefore recommend that you verify the information on this datasheet with other sources before making any decisions based on this information. Additional information about the product can be found on our website.