Our retail price is a recommendation only. Prices in offer may differ. All prices indicated 0,00 € will follow in the offer.



BENNING MULTIMETER MM 6-2 0.000 V-1,000 V AC/DC TRUE RMS

SKU: 4014651440876

Multimeter MM 6-2 0.000 V-1,000 V AC/DC TRUE RMS

Categories: Measuring and testers for electrical installation, Multimeters and accessories

Product Features: Measuring technique: TRUE RMS
Brand: BENNING
Nominal voltage range: 0.000 V-1,000 V AC/DC
Measurement category: CAT IV 600 V
Datasheet

Scope of delivery:
1,00 ST Multimeter MM 6-2 0.000 V-1,000 V AC/DC TRUE RMS |

PRODUCT DESCRIPTION

With illuminated 4-digit LCD display (6,000 points) with bar graph
- Continuity testing via red LED and buzzer
- Diode testing
- AutoV function for automatic AC/DC voltage detection
- LoZ low input impedance for suppressing interspersed capacitative/inductive voltages
- Integrated volt sensor signals non-contact phase voltages and cable breaks in lines (optical/acoustic)
- Single-pole phase testing
- Automatic range selection
- Automatic switch-off
- Measured value (HOLD peak value memory (PEAK relative measurement (REL)
- Measurement category CAT IV 600 V, CAT III 1000 V Measuring ranges: Direct voltage: 100 µV-1,000 V, alternating voltage: 100 µV-1,000 V, direct current: 1 mA-10 A, alternating current: 20 mA-10 A, resistance: 0.1 -40 M, frequency: 0.01 Hz-100 kHz, capacitance: 1 nF-10 mF Further technical information:
- Width: 82mm
- Length: 163mm
- Height: 50mm Supplied with protective rubber frame with magnetic hanger, bag, battery (9 V block LR

Copyright © 2023 Actik Tools All rights reserved

61 measuring lines Replacement battery, see article no. 4000 876 104 Note on the disposal of batteries and rechargeable batteries As we sell batteries and rechargeable batteries and devices that contain batteries and rechargeable batteries, under the German Battery Act (BattG we are obliged to draw your attention to the following: The symbol of the waste bin with the X through it on batteries and rechargeable batteries means that they must not be disposed on in household waste after consumption. If batteries or rechargeable batteries contain mercury, cadmium or lead, you will find the chemical symbol (Hg, Cd or Pb) under the symbol of the waste bin with the X through it. Every user of batteries or rechargeable batteries is legally obliged to return old batteries and rechargeable batteries. They can be returned, free of charge, to the retailer or another collection point near you. You can obtain the addresses of suitable collection points near you from your local government authority. In the case of batteries that contain more than 0.0005 percent by mass mercury, more than 0.002 percent by mass cadmium or more than 0.004 percent by mass lead, the chemical symbols of the respective harmful substance used are indicated under the waste bin symbol. The chemical symbols have the following meaning: Pb: Battery contains lead Cd: Battery contains cadmium Hg: Battery contains mercury

PRODUCT DATASHEET LEGAL NOTE

Please note that the information on this datasheet is provided without warranty and is intended only as non-binding information about the product. Any liability for damages or losses that may arise from the use of this information is excluded. We therefore recommend that you verify the information on this datasheet with other sources before making any decisions based on this information. Additional information about the product can be found on our website.

Copyright © 2023 Actik Tools All rights reserved