



Our retail price is a recommendation only. Prices in offer may differ. All prices indicated 0,00 € will follow in the offer.



ROBERT BOSCH POWER TOOLS GMBH CHARGER GAL 18V6-80

SKU: 4059952519135

Charger GAL 18V6-80

Categories: [Battery-powered tools](#), [BOSCH professional](#)

Product Features: Packaging dimensions (width): 243 mm
Packaging dimensions (length): 310 mm
Packaging dimensions (height): 220 mm
Packaging dimensions (width x length x height): 243 x 310 x 220 mm
Battery voltage: 18.0 V
Battery charging voltage, from: 14,4 V
Battery charging voltage, up to: 18 V
Battery charging voltage: 14.4 - 18 V
Charge current: 8,0 A
Charg. time at bat. cap. 2.0 Ah (80%) approx.: 16
Charg. time at bat. cap. 2.0 Ah (100%) approx.: 24
Charg. time at bat. cap. 2.0 Ah (80%/100%) approx.: 16/24 min
Charg. time at bat. cap. 4.0 Ah (80%) approx.: 23
Charg. time at bat. cap. 4.0 Ah (100%) approx.: 37
Charg. time at bat. cap. 4.0 Ah (80%/100%) approx.: 23/37 min
Charg. time at bat. cap. 5.0 Ah (80%) approx.: 28
Charg. time at bat. cap. 5.0 Ah (100%) approx.: 47
Charg. time at bat. cap. 5.0 Ah (80%/100%) approx.: 28/47 min
Charg. time at bat. cap. 6.0 Ah (80%) approx.: 32
Charg. time at bat. cap. 6.0 Ah (100%) approx.: 57



Charg. time at bat. cap. 6.0 Ah (80%/100%)
approx.: 32/57 min
Charg. time at ProCORE18V 4.0 Ah (80%)
approx.: 32
Charg. time at ProCORE18V 4.0 Ah (100%)
approx.: 50
Charg. time ProCORE18V 4.0 Ah (80%/100%)
approx.: 32/50 min
Charg. time at ProCORE18V 8.0 Ah (80%)
approx.: 42
Charg. time at ProCORE18V 8.0 Ah (100%)
approx.: 68
Charg. time ProCORE18V 8.0 Ah (80%/100%)
approx.: 42/68 min
Charg. time at ProCORE18V 12.0 Ah (80%)
approx.: 65
Charg. time at ProCORE18V 12.0 Ah (100%)
approx.: 96
Charg. time ProCORE18V 12.0 Ah (80%/100%)
approx.: 65/96 min
Weight: 2 kg
Product category subdivision: Charger
Positioning: Continuous charging for non-stop work - multi-bay charger with 6 battery interfaces
User benefit incl. Reason to believe: Fast charging speed with 8A current - ProCORE18V 8.0Ah charges to 80% in 42 min
User benefit incl. Reason to believe: Efficient charge - 2 charging cycles ensure continuous work
User benefit incl. Reason to believe: Priority Start Button - easy prioritisation of a selected battery
Positioning (BE): Continuous charging for non-stop work - multi-bay charger with 6 battery interfaces
User benefit incl. Reason to believe (BE): Fast charging speed with 8A current - ProCORE18V 8.0Ah charges to 80% in 42 min
User benefit incl. Reason to believe (BE): Efficient charge - 2 charging cycles ensure continuous work
User benefit incl. Reason to believe (BE): Priority Start Button - easy prioritisation of a selected battery
Title: Charger GAL 18V6-80 Professional
Novelty: no



Novelty until: 01.10.2020
Scope of supply: Cardboard box
Scope of supply: L-BOXX adapter for GAL
18V6-80
SOL Date: 01.06.2020

Scope of delivery:
1 ST Charger GAL 18V6-80 |

PRODUCT DESCRIPTION

Charger GAL 18V6-80, The GAL 18V6-80 offers continuous charging on the job or overnight in two cycles. The first cycle charges up to six batteries sequentially up to 80%. Cycle two then completes the process, charging all batteries to 100%. Thanks to an 8A charging current, ProCORE18V 8.0Ah batteries load up to 80% in just 42 minutes. Charge-level indicators with 5 LEDs on each charging interface display precise charging progress. With a Priority Start Button for each interface, the cycle can be interrupted to start charging the selected battery immediately. It is compatible with all Bosch Professional 18 V batteries (Professional 18V System). Fixing the multi-bay charger to an L-BOXX avoids potentially harmful movements when transporting. The charger's handle features pegs that allow its cable to be wound neatly in place for storage and safe transportation. Cardboard box; L-BOXX adapter for GAL 18V6-80

Article ID: 1600A01U9L

PRODUCT DATASHEET LEGAL NOTE

Please note that the information on this datasheet is provided without warranty and is intended only as non-binding information about the product. Any liability for damages or losses that may arise from the use of this information is excluded. We therefore recommend that you verify the information on this datasheet with other sources before making any decisions based on this information. Additional information about the product can be found on our website.