Our retail price is a recommendation only. Prices in offer may differ. All prices indicated 0,00 € will follow in the offer.



ROBERT BOSCH POWER TOOLS GMBH RADIO GPB 18V-2 C

SKU: 4059952507811

Radio GPB 18V-2 C

Categories: Battery-powered tools, BOSCH professional

Product Features: Packaging dimensions (width): 200 mm
Packaging dimensions (length): 385 mm
Packaging dimensions (height): 162 mm
Packaging dimensions (width x length x height): 200 x 385 x 162 mm
Battery voltage: 18.0 V
Radio frequency range FM, from: 87,5 MHz
Radio frequency range FM, up to: 108 MHz
Radio frequency range FM: 87.5 - 108 MHz
Station presets FM: 8
Input voltage(s) of battery, from: 18 V
Input voltage(s), battery: 18 V
Station presets: 8
Input voltage(s), mains, from: 100 V
Input voltage(s), mains, up to: 240 V
Input voltage(s), mains: 100 - 240 V
Output voltage(s), mains: 18 V
Weight excl. battery: 2,5 kg
Rated power of amplifier (in mains operation): 15 W
Product category subdivision: Radio
Positioning: Flexible and handy: portable radio that rocks every jobsite
User benefit incl. Reason to believe: Versatility thanks to wide range of compatible sources, including Bluetooth®, FM, and AUX
User benefit incl. Reason to believe: Features intuitive operation and quick setup in combination with a handle and hook for vertical and horizontal placement
User benefit incl. Reason to believe: Unique

Copyright © 2023 Actik Tools All rights reserved

stereo sound due to the possibility to couple two radios with one smartphone
Positioning (BE): Flexible and handy: portable radio that rocks every jobsite
User benefit incl. Reason to believe (BE): Versatility thanks to wide range of compatible sources, including Bluetooth, FM, and AUX
User benefit incl. Reason to believe (BE): Features intuitive operation and quick setup in combination with a handle and hook for vertical and horizontal placement
User benefit incl. Reason to believe (BE): Unique stereo sound due to the possibility to couple two radios with one smartphone
Title: Radio GPB 18V-2 C Professional
Novelty: no
Novelty until: 07.09.2022
Scope of supply: Cardboard box
Scope of supply: 1 x DC-in power adapter (spare part number 1 619 PB4 880)
Scope of supply: 1 x AUX cable
Scope of supply: 1 x 3 V CR2032 lithium button cell battery
SOL Date: 07.06.2022

Scope of delivery:
1 ST Radio GPB 18V-2 C |

PRODUCT DESCRIPTION

Radio GPB 18V-2 C, The GPB 18V-2 C Professional is the flexible and portable solution to fill the air of any working environment with music and sound via Bluetooth®. Compatible with a wide range of sources, including Bluetooth®, FM, and AUX, this set is as versatile as the art of music itself. It is powered via 18 V batteries or main AC and provides intuitive operation, quick setup, USB charging and IP 54 protection. It can be placed vertically as well as horizontally and it has both a handle and a hook for easy transportation and storage, further favoured by the radios compactness. The possibility of coupling two radios with one smartphone facilitates unique stereo sound. This unit is ideal for providing jobsites with radio entertainment as well as smartphone-sourced music. It is compatible with Bosch Professional 18 V batteries (1.5 - 8 Ah). The GPB 18V-2 C Professional´s two speakers with a total of 15 W make for splendid sound, while additional passive radiators provide enhanced bass response. Cardboard box; 1 x DC-in power adapter (spare part number 1 619 PB4 880); 1 x AUX cable; 1 x 3 V CR2032 lithium button cell battery

Article ID: 06014A3000

Copyright © 2023 Actik Tools All rights reserved

PRODUCT DATASHEET LEGAL NOTE

Please note that the information on this datasheet is provided without warranty and is intended only as non-binding information about the product. Any liability for damages or losses that may arise from the use of this information is excluded. We therefore recommend that you verify the information on this datasheet with other sources before making any decisions based on this information. Additional information about the product can be found on our website.

Copyright © 2023 Actik Tools

All rights reserved